



*Applicable for Guardian 315, 415, 425, 615, 716, 628 openers

#Applicable for Guardian PWLLSTN and DLXWLLSTN Door Control Consoles

Applying the Door Control Console Plug to pre-wired installation

1. Properly connect one end from the pre-wired bell wires to the screw terminals on the back of the Door Control Console, note the polarities.
2. Splice 0.4inch from the other end of the pre-wired bell wires, and fully insert the wires with respect to the polarities from the Door Control Console as well as the short wire with plug.
3. Press the taps on the open end of the wire connector.
4. Fully insert the wires with respect to the polarities from the Door Control Console as well as the short wire with plug.
5. Connect the Door Control Console Plug to the Door Control Console terminal on the back of the opener.

Attention: Make sure the polarities on both the wiring and the connector according to above instructions, and test the Door Control Console functions upon completion.